DATA MODEMS

Contents

- 1. GENERAL
- 2. INTERFACES
- 3. CODES
- 4. DATA MODEMS
- 5. CLASSIFICATION AND TYPES OF DATA MODEMS
- 6. ACOUSTICALLY COUPLED DATA MODEMS
- 7. DATA SYSTEMS
- 8. APPLICATION OF DATA MODEMS
 - Table 1 Voice Bandwidth Data Channel and C-Type Conditioning
 - Figure 1 American Standard Code for Information Interchange (ASCII)
 - Figure 2 10 Bit Asynchronous Transmission Code
 - Figure 3 Acoustically Coupled Analog Data Modem
 - Figure 4 Factory Data System
 - Figure 5 Pushbutton Dial Characters and Frequencies
 - Appendix I Terminology Definitions Commonly Used in Data Communications
 - Appendix II Quick Reference to Bell System Data Modems
 - Appendix III Buyer's Guide to Data Modems and Acoustic Couplers

1. GENERAL

- 1.1 This section provides REA borrowers, consulting engineers and other interested parties with information for use in the design and construction of REA borrower's telephone systems. It discusses the classifications, types, and uses of data modems, data interface considerations, and applications of data systems to rural telephone systems. This section treats primarily the situation where a customer leases data equipment and services from the telephone company. It does not apply specifically to data equipment and services needed by the telephone company for its own operation. The transmission aspects of data are dealt with in this section only to the extent necessary to clarify interface and terminal functions. Data transmission per se will be covered in a separate TE & CM section. A summary of terminology and definitions commonly used in data systems is covered in Appendix I.
 - 1.2 To date, not many loans have included data services. A large potential demand for data services exists in rural areas but aggressive

action by the telephone company is needed to develop this potential into firm orders for data service. Borrowers and their engineers must know and understand the customer's needs and must have sufficiently detailed knowledge of available data equipment and applications to adequately meet those needs. If the borrowers and their engineers are unable to meet this demand, subscribers will turn to other sources, thus causing a loss of revenue for the telephone company.

- 1.3 This section is concerned primarily with the equipment that forms the interface between a customer owned business machine and the communication channel. This interface equipment is called a data modem. The principal function of such equipment is to take the output of a business machine such as a computer, convert it into a form suitable for transmission over a communication channel, and reconvert it to business machine form at the distant end. Because the desirability of using ordinary voice frequency loop plant as a circuit facility for data transmission is frequently an overriding consideration, most applications are expected to require slow and medium speed data sets.
- 1.4 A wide variety of data modems and terminal equipment is being marketed in increasing quantities. When associated with a data business machine and a data modem, every ordinary telephone station installation could become a point of entry for data to a communications facility, whether it be a public switched network line or a leased private line. The simplest form of data modem is the pushbutton telephone set which can be used to access a computer, provide input data to the computer, and (if the computer terminal is properly equipped) receive data output from the computer.
- 1.5 "Data Phone"*service is a tariffed service offering of the Bell System for the transmission of data over the switched telephone (DDD) network. This service, like regular voice service is offered on a monthly rental basis, with the circuit facilities and all necessary equipment (except the customer owned business machines) being furnished and maintained by the Bell System operating telephone company. "Data Phone"*service has grown rapidly since its introduction in 1958 because it is a versatile and economical means of transmitting business data from point to point.
- 1.6 It is important that the manager study the immediate and probable future data system requirements of his customers. He must also become familiar with modem capabilities and features, and the required characteristics of the telephone loop and trunk circuits. Detailed specific information on particular makes and types of modems is readily available from the equipment manufacturer. Circuit facilities commonly

^{*}AT&T Registered Service Mark and Trademark

used for data communications include: the public switched network; dedicated leased lines without conditioning; and dedicated conditioned leased lines. Two wire lines are usually required; however, four-wire circuits may be required in some instances.

1.61 Conditioned lines are point-to-point circuits which have specified transmission characteristics quoted in the applicable tariffs. The detailed specifications for Bell System private leased lines can be found in the Bell System Technical Reference, Publication 41004 entitled "Transmission Specifications for Voice Grade Private Line Data Channels." This document and other "Bell System Technical References" can be obtained for \$1.50 each from:

American Telephone and Telegraph Co. Supervisor - Information Distribution Center Room 208 195 Broadway New York, N. Y. 10007

- 1.611 Publication 41004 gives the specific characteristics required for data transmission channels for the various data sets. Attenuation, bandwidth, noise, phase jitter, envelope delay distortion, echo, impedance, and power levels are specified. If the channels in question do not meet the requirements, conditioning must be applied to correct them. Abbreviated specifications for several different types of conditioning are shown in Table 1.
- 1.612 Because of the broad, flat, pass band and low delay distortion of D66 loaded loops and trunks it is probable that many cable circuits in REA borrowers' systems can be used for low and medium speed data transmission without conditioning. Where a number of data channels are needed between two points carrier channels are preferred if they meet the specified data transmission requirements. These characteristics of carrier channels can be obtained from the carrier manufacturers.
- 1.613 Neither cable pairs nor carrier channels should be used for data transmission without first measuring attenuation, delay distortion, and impulse noise. A circuit facility which is known to be a good voice channel may not be satisfactory for data transmission because delay distortion, impulse noise, and phase jitter, which are relatively unimportant in voice communications, may make a good voice channel totally unsatisfactory as a data channel.
- 1.62 When planning a data system, the factors of economics, expandability, redundancy, reliability, and service must be considered as well as the technical characteristics of the equipment. Under economics, factors such as the cost of leasing from the telephone company versus purchasing of equipment by the customer are important. Modems, like most of the other equipment required to develop a data system, can generally

be either purchased or leased from the manufacturers or suppliers. It is important to have a system that can be economically modified, either expanded or reduced, to meet the customer's changing needs. The need for redundancy varies greatly depending on a number of factors. For example, if very important "real time" data is involved, complete redundancy and substantially errorless data transmission are important. In other situations continuous operation 24 hours per day 7 days per week may be important. Where an occasional system "down-time" can be tolerated, and where intermittent rather than continuous transmission is involved, less reliable, less costly equipment can be used. However, if poorer quality equipment is used, error rates may become unacceptable, and retransmission costs may become excessive.

INTERFACES

- 2.1 The rapid growth in data communications and technology has been aided and guided by standards, principally issued by the Electronics Industries Association (E.I.A.). This Association has issued a number of important standards on interface considerations which enhance compatibility among different makes and types of equipment. Standard RS-232-C, "Interface Between Data Terminal Equipment and Data Communication Equipment Employing Serial Binary Data Interchange" was issued in August 1969. It specifies the functional and electrical characteristics of all interchange circuits between the data terminal equipment and the data communications equipment. It also specifies that the mechanical interface between the business machine and data set be a multi-pin plug-in connector. Certain pins have specifically designated functions; such as, Pin 1 is "Protective Ground;" Pin 2 is "Transmitted Data;" Pin 3 is "Received Data;" and so forth. This standard is now well recognized and followed by most suppliers for speeds up to about 20,000 bits per second (bps).
- 2.2 The line sides of data modems interface with telephone circuits. For data speeds up to 2400 bps on either a point-to-point private line or on the public switched network, regular voice frequency loop and trunk plant circuit facilities are generally adequate.
- 2.3 For data speeds in excess of 2400 bps, data modems usually must work into conditioned lines. However this situation is changing rapidly as new data modems are developed. Some data modems are available today which operate on unconditioned lines at speeds of 4800 bps or higher.

3. CODES

3.1 The business machines (terminals), at each end of a data communication circuit, "talk" to each other by means of a machine language comprised of a specific code transmitted in accordance with a specific format and a specific rate of speed. The basis of all effective data trans-

mission is the standardization of codes. The first data transmission code, Morse Code, used dots and dashes for characters. The most common business equipment code in use during the early sixties was the Baudot code, as used by teleprinters. The Baudot code has five bits per character and is usually encoded as a paper tape having five rows or "levels." With the introduction of computer processing, codes have been developed which use a greater number of bits per character. Examples of these codes are "Fieldata," six bits per character; IBM "Teleprocessing," eight bits per character; and the American Standard Code for Information Interchange (ASCII), basically seven bits per character. When transmitting ASCII code, an eighth bit is used as a check, or parity bit, for error correction purposes. This eighth bit is not actually part of the basic code structure. There are a total of 128 specified combinations covering the alphabet (both upper and lower case), the ten numerals, and 66 special symbols. The ASCII code card is illustrated in Figure 1, and can be obtained from EIA or from computer and data set manufacturers.

3.2 The Baudot and ASCII codes are basically designed for transmission of the English alphabet. Other codes are used for special purposes, such as the "Extended Binary Coded Decimal Interchange Code." (EBCDIC). Here, the numbers from 00 to 99 can be used to identify letters, numbers, and symbols. The format characteristics of the code will vary depending upon a particular terminal equipment, purpose, and design. A specific code format is required for error control and is also required for compatible operation. However, code compatibility alone does not insure compatible operation. Supervisory ("handshake") signals, speed, and mode of operation must also be compatible. It is particularly important to check all aspects of compatibility when a system is being designed which involves equipment from different manufacturers. It is anticipated that this situation will occur frequently because there will be many cases where one end of a data circuit will be furnished by a Borrower and the other end will be furnished by the Bell System or some other telephone company.

4. DATA MODEMS

- 4.1 The term "Modem" is actually a contraction of the two functions to be performed, i.e., modulating and demodulating. The terms "data set" or "data subset" are also used to identify a modem. Data modems can be classified as analog or digital depending on the nature of the customer's signal.
- 4.2 A digital data modem is a device which accepts the d.c. pulse output from a computer, teletype, or other business machine equipment and converts this output to an audio signal or frequency which is more suitable for transmission over voice grade lines or other communication facilities. At the receiving end, these signals are then reconverted to their original dc pulse state, making the data once again usable for terminal equipment.

Digital data modems usually are classified by speed range. Low speed is up to about 300 bps. Medium speed has been from 300 to 2400 bps but recent development of adaptive automatic equalizers have made it possible to operate this medium speed equipment up to 9600 bps under some conditions on paired cable or carrier facilities. The term "high speed" data is usually applied to bit rates which require broad band transmission facilities.

- 4.3 Analog data modems accept data in the form of a continuously variable signal and processes the signal for transmission over the telephone circuit. Analog data are usually represented by variables such as voltage, resistance, phase rotation, etc. Some uses of analog modems are for transmitting facsimile, certain types of medical data, temperatures, and pressures.
- 4.4 There are four basic types of modem designs, classified with respect to their associated method of modulating the signal presented to the telephone line.
 - 1. Amplitude Modulation (AM)
 - 2. Frequency Modulation (FM)
 - 3. Phase Modulation (PM)
 - 4. Pulse Code Modulation (PCM)

A description of these follows:

- 4.41 The AM Modem transmits a constant frequency to the telephone line.

 Amplitude varies depending upon the value of the dc binary information. For example, a dc "l" level from the business machine will be converted by the modem to a full amplitude tone while a dc "O" level will be converted to a lower amplitude tone. AM is generally used for low speed data transmission (up to 300 bps), and is the least complex to design and manufacture. However, AM modems tend to react to burst or impulse noise which varies the amplitude and energy level of the transmitted signal. For example, impulse noise coincident with an "O" level can raise the amplitude so that the demodulator interprets the received signal as a "l" level.
 - 4.42 The FM modem transmits a constant level of amplitude to the telephone line, but indicates a "1" by one frequency and a "0" by a different frequency. For example, a dc "1" level will be frequency #1, while a dc "0" level will be frequency #2. FM is generally used for medium speed data transmission in the 300 to 1800 bps range and is more complex to manufacture than AM modems. The FM modem has a higher immunity to impulse noise than the AM modem.
- 4.43 The PM modem transmits a constant amplitude and frequency to the telephone line; however, the phase changes depend upon the value of the dc binary information. For example, a dc "1" level could be phase 0° while a dc "0" level could be shifted in phase 180°, or some other value, from the previous phase. PM is generally used for data transmission in the 2000 bps to 4800 bps range, and is quite complex in design and manufacture. PM modems have excellent noise immunity characteristics, since they use constant amplitude and frequency, and generally higher information handling ability

than AM or FM systems, but are more susceptible to impaired performance from phase jitter.

- 4.44 Pulse Code Modulation (PCM) transmission is a type of transmission that requires a much greater bandwidth than voice. Bandwidths exceeding the bandwidth of a single voice channel (about 4 kHz) are called wideband modems. Wideband modems are not true modems since they do not contain a modulator or demodulator, but they do condition a digital signal for transmission over the telephone network.
- 4.441 An important advantage of PCM is that once all the signals are in digital form (voice, telegraph, television, facsimile, data, and others) the signals can be time division multiplexed and carried over the same transmission medium without interfering with each other. The PCM systems are expected to have a major impact on wideband data transmission. For example, the PCM-Tl digital transmission system has a line rate of 1.544 megabits per second. Ninety percent of this spectrum width can be used for data transmission. By the use of various modems, eight 50 kb/s channels, two 250 kb/s channels, or one 500 kb/s channel can be accomposed on a single Tl carrier system. With special arrangements, the full bandwidth could be used. Newer PCM-T2 and T4 digital transmission systems will operate at 6.3 and 281 megabits per second respectively.
- 4.5 While standardized codes and formats are important to the intelligibility of a transmitted signal, compatible timing is equally important. Modems are classified with respect to method of timing as: (a) asynchronous, or (b) synchronous.
- 4.51 Information may be transmitted in a bit-serial asynchronous mode, (with start and stop bits). When asynchronous transmission is used, a mark condition is maintained on the line during any idle state. When a character is to be transmitted, a space condition is sent as the first bit to indicate the start of a character. This is followed by an appropriate mark or space condition for each data bit of the character. The last bit of the character is followed by a stop pulse which is always marking and which may be equal to or longer than the bit length. The line remains in a mark condition until the next character is ready (See Figure 2). These modems operate very reliably within their stated limits and are generally used at transmission rates up to 1800 bps.
- 4.52 Information may be transmitted in the synchronous mode. This technique transmits bits at a constant rate as opposed to asynchronous transmission. When synchronous transmission is used, the transmitting terminal and the receiving terminal are timed from a synchronized clock and the bit code is transmitted without start or stop codes. The start of the message is a series of prescribed synchronizing code characters, called SYNC code. The receiving modem has the capability of establishing the timing synchronization of its clock with that of the transmit modem by sampling the received bits. The receiving terminal interprets the first space bit transmitted as the start of the character signal and samples each of the following bits at a rate dictated by the receiver's clock. As the bits are sampled,

the mark or space condition is transferred from the line and stored within the receiving terminal. Characters transmitted via this bit stream have the last data bit of one character immediately followed by the first bit of the next succeeding character. The receiving terminal has the necessary logic required to count up the bits in a character and separate individual characters from the incoming bit stream. Synchronous modems are available with bit rates of 1200 bps and higher. These modems operate only at specified speeds. A higher transmission efficiency can be achieved since the only noninformation parts of the transmission are the parity bits and control codes, such as the SYNC code.

4.6 Some modems also contain line equalizers or line conditioners as part of their design. The equalizers are intended to complement, not replace, common carrier provided line conditioning. These modem equalizers essentially perform the "fine tuning" required for higher transmission speeds. Modem equalizers can be either manual or automatic. With automatic equalization, the receiving modem can sample the delay variations present in a received signal and automatically introduce delay at the appropriate frequencies to insure that all frequencies are received at the same time.

5. CLASSIFICATION AND TYPES OF DATA MODEMS

- bers to designate different data speeds and types of data modems. Most of the independent data modem manufacturers have used this same basic designation number series to identify their equivalents of the Western Electric modems. In many instances the same designs are used so that the independent products are completely compatible with the corresponding Western Electric modems. It is, therefore, practicable in many instances for independent equipment to be used on one end of the circuit and Western Electric equipment on the other end.
- group has basically similar characteristics and is normally assigned a special hundred series code. Numeric codes within each series are applied to data modems to designate specific models. For example, a 101 data modem has low speed, serial transmission techniques; but it differs slightly from other sets in the same series, such as 103 data modem. In addition, a letter suffix such as a 103A or 103F is added to the numeric code to indicate the modifications and variations of a particular modem or in some cases, to differentiate between a transmitter and a receiver. A further breakdown is sometimes provided by including an additional numeric suffix to indicate will depend on the application for which it is intended. The type and quantity of data to be transmitted, the speed and accuracy desired, and the type western Electric modem series is as follows.

- 5.03 The 100 series data modems are generally low speed transmitter-receiver modems. The type of transmission is bit-serial with a bit rate of 0-300 bps, asynchronous on the voice switched network (Direct Distance Dialing, DDD) and Private Line (PL) facilities and 0-150 bps, non-synchronous on teletype facilities. The private line facility may be a line equivalent to a Bell System 2001 or 3002 type conditioned line (paragraph 1.61) depending on the modem model to be used. Modem operation is half-duplex or full-duplex on two wire facilities. These modems are primarily used with teletypwriters and other types of business machines. Data modems used on the DDD network generally use a separate six-button key telephone set or Auxiliary set for alternate voice/data operation. Dialing methods may be either rotary, pushbutton, rotary with card dialer, or pushbutton with card dialer. Generally, the buttons are labeled DATA, CLEAR/TALK, TEST, (spare), (spare), and AUTO (for automatic answer) although other variations may exist, depending upon the data modem options. A loudspeaker with a volume control knob may be used for monitoring call progress tones when calls are originated in the data mode. The 100 series data modems may also be used in multiple data modem installations.
- 5.04 The 200 series data modems are generally medium speed transmit and/or receive modems. The type of transmission is bit-serial. Bit rates may be up to 3600 bits per second on DDD and up to 7200 bits per second on private line facilities using synchronous and non-synchronous modes, depending on the modem model used. The private line facility may be a line equivalent to a Bell System 2001 or 3002 type line with no conditioning or with Cl or C2 conditioning (see paragraph 1.61). Modem operation is half duplex on two wire or full duplex on four wire facilities. These modems are primarily used with various types of business machines. Each data modem used on the DDD network generally uses a separate six-button telephone set or Data Auxiliary set with button designations and a dial. A loudspeaker similar to that described under the 100 series of Data Modems is optional. Synchronous modems require a clock or timing signal either generated internally by the modem or provided by the data processing equipment. This clock is used to sample the d.c. signal and activate the modulator. At the processing location the clock sends a signal to the data processing equipment when each newly received bit has been demodulated.
- 7.05 The 300 series data modems are generally higher speed transmitreceive modems. The type of transmission is bit-serial. Bit rates available, at present, include 19,200, 40,800, 50,000, 230,400, and 460,800 bps synchronous on private line facilities. The private line facility generally may be a line equivalent to a Bell System 5700 or 8800 type. Modem operation is half duplex on two wire and full duplex on four wire facilities. These modems are primarily used with high speed business machines. These data modems normally require a separate Data Auxiliary set containing six buttons and a rotary or push-button dial similar to that described under the 100 series of data modems. The 300 series also includes wideband data modems for use in the transmission of serial binary synchronous or nonsynchronous

high speed data over half group, group, or supergroup carrier facilities. Wide-band data applications require a high degree of custom engineering and the installation of special equipment for higher speeds.

- 5.06 The 400 series data modems are generally low and medium speed separate transmit and receive modems. The type of transmission is parallel by bit, serial by character; that is, the characters are sent sequentially and the bits within the characters are dealt with simultaneously (not one after another). Bit rates available, at present, include 40, 90, 130, and 600 bps nonsynchronous on DDD and private line facilities. The private line facility generally may be a line equivalent to a Bell System 2001 or Type 3002, with or without Cl conditioning. Modem operation is half duplex on two wire and full duplex on four wire. These modems are primarily used on low speed non-synchronous data collection devices, alarm reporting terminal equipment, and telemetry devices. The telephone handset, buttons, and dial may be integrated into the data set housing or may be in a separate Data Auxiliary set.
- 5.07 The 500 series data modems are wideband modems for high speed parallel applications with synchronous or nonsynchronous operation. Western Electric does not have any 500 series equipment available at the present time, but 500 series modems are available from one or more independent suppliers.
- 5.08 The 600 series data modems are generally intended for analog transmission on DDD and private line facilities. The private line facility may be a line equivalent to a Bell System 2001 or 3002 with no conditioning. Modem operation is half duplex on two wire operation. These modems may be used for reception and transmission of handwriting, facsimile, and of medical diagnostic data, such as electrocardiograms. Data sets in this series that are intended for fixed installation usually have a complete telephone set integrated into the data set housing. Portable battery operated data sets for transmission of medical data are also available in this series for use at the patient's bedside. These modems are acoustically coupled to the telephone line. Acoustically coupled modems are discussed in paragraph 6.
- 5.09 The 700 series is reserved for wideband analog modems. At the present time there are no modems available in this series.
- 5.10 The 800 series covers auxiliary units used in conjunction with other data modems and are generally automatic calling units. These units usually contain automatic dialing and control equipment, and are needed when automatic calling is required.
- 5.11 The 900 series covers interface adapters and test equipment.
- 5.12 Appendices II and III are reprinted from a copyrighted article entitled "Data Modems '73" by Warren G. Bender in the January 1, 1973, issue of the magazine "Telephone Engineer and Management." The information in these

appendices was obtained from a survey by TE & M of every known U. S. supplier of data modems and acoustic couplers. New models of data modems are being developed constantly and some of the older models are being superseded. Therefore, neither TE & M nor REA can be responsible for the accuracy or completeness of the information. The material, however, should give the reader a comprehensive indication of the equipment that is generally available. Appendices II and III were reprinted by permission of "Telephone Engineer and Management."

6. ACOUSTICALLY COUPLED DATA MODEMS

- 6.1 Most types of data modems are hard wired into the circuit between the customer owned business machine and a network protection device, or directly to the telephone line. Some types, however, are coupled to the telephone line through the telephone handset by means of an acoustic coupler that is built into the data modem. The quality of the transmitted signal from acoustically coupled modems is poorer than that from a hard wired modem because it is affected by the distortion and variability of the carbon transmitter of the telephone set. Acoustically coupled data modems should not be confused with "data couplers" that constitute a portion of a "Data Access Arrangement." Data couplers, used in "Data Access Arrangements" are usually hard wired and provide protection to the DDD network when a customer owned data modem is used under present Bell System tariffs. Data Access Arrangements will be discussed in a separate TE & CM section on inter-connection of customer owned equipment to telephone company lines.
- 6.2 Acoustically coupled data modems, in addition to the electronic components, generally include a small electro-acoustic transducer (speaker) mounted in a housing that forms a sound muffling cradle for the telephone handset. When the handset is placed in the cradle, the handset transmitter is acoustically coupled to the speaker in the modem. The acoustic data set accepts information from the business machine in the form of d.c. electrical pulses (binary digits or bits), converts these pulses into audio-frequency electrical signals, then to audio tones in the speaker. The audio tones are picked up by the telephone transmitter, reconverted to voice frequency electrical tones, and are transmitted over the telephone circuit. Acoustically coupled data modems offer convenient, reliable, and portable service. Some modems can either transmit or receive (half duplex) at any data rate up to 300 bps, or transmit and receive simultaneously (full-duplex) at rates up to 150 bps, using different frequency bands for sending and receiving. Modems may be powered from the terminal device or from a local 115 volt 60Hz commercial source through an auxiliary assembly. Batteries are not normally used except where portability is important as in the patients'bedside models.
- 6.3 One type of data modem commonly used for transmitting electro-cardiograms (EKG) is an analog device which functions as follows: The analog signal output from the EKG machine is fed into a dc coupled differential

amplifier in the data modem (Figure 3). The output of the differential amplifier is proportional to the input signal and is applied to a voltage-controlled oscillator whose normal frequency of about 2000 Hz varies linearly with the input signal voltage. This varying frequency signal is converted to acoustic tones by an electro-acoustic transducer (speaker) which is acoustically coupled to the transmitter of the telephone hand set. The acoustic signal is then converted back to an electric signal by the carbon transmitter and is sent over the telephone line to the receiving modem. There it is recovered as a varying voltage which reproduces the original signal at its original amplitude in the receiving EKG machine. A reverse channel receiver is also included in these modems to permit the receiving location to alert personnel at the transmitting location. The reverse channel signal is a single voice frequency tone which actuates supervisory signals at the data transmitting location. (See Figure 3.)

6.4 Portable data stations consisting of a 600 series data modem combined with a business machine can be moved from office to office, or used in remote locations where a fixed data station is not available.

7. DATA SYSTEMS

- 7.1 There are many different equipment units which can be assembled into many combinations to produce data systems to accomplish specified objectives. It is, therefore, impractical in this section to give detailed engineering information on each type of equipment.
- 7.2 The Bell system uses many different types of data systems and has published Technical References which give detailed information on each of its data modems that are in common use. These Technical References are listed in catalog PUB 40000, and are available to Borrowers and Engineers from American Telephone and Telegraph Company as indicated in paragraph 1.61. Independent equipment suppliers furnish detailed information on their equipment and generally adequate system design information can be obtained on request.
- 7.3 One practical approach that a borrower faced with a request for data service from a customer could follow would be to request the services of a representative of an independent modem supplier. Another approach would be as follows:
 - (1) Determine the customer's basic needs in sufficient detail to ascertain what series of Western Electric equipment would be required if Western equipment were to be used.
 - (2) Purchase the applicable "Technical References" from the A. T. & T. Co. to obtain the necessary technical information to develop a firm system proposal.

(3) Obtain from an independent supplier, equipment which is equivalent to the applicable Western Electric equipment.

8. APPLICATIONS

- 8.1 There are a number of different types of businesses in areas served by rural telephone systems that are good prospects for data systems including the following:
 - A. Branch Banks
 - B. Warehouses
 - C. Factories
 - D. Branch Offices of companies (such as insurance, brokerage, and autorental).
 - E. Doctors' Offices
 - F. Hospitals
 - G. Branch Retail Stores
 - H. Public Utilities Offices
 - I. Transportation Companies
 - J. Law Enforcement Agencies
- 8.2 Some examples are discussed below.
- 8.21 A typical application for a branch facility of some centralized business would consist of one or more data input devices in each branch location that would send data to a central computer. Some of these installations would also need a data receiving capability in order to receive data from the computer. In the branch bank application the data system might provide push button telephone sets to enable each teller to query a central computer regarding a customer's account. The central location would have to be equipped with rather elaborate voice-answerback facilities to enable the teller to receive the information verbally through his push button telephone set.
- 8.22 A factory installation might consist of push button telephone sets installed at various locations throughout the plant. Each of the push button sets would have direct access to a PABX and through a traffic concentration group of trunks, from the PABX to the computer as shown in Figure 4. The PABX trunks would be terminated in Western Electric #403D or #403E (or

yan and one gastagasayand and and and bot book and could

equivalent) data set tone receivers. These tone receivers are required at the computer center to decode and translate the incoming push button tone signals into a form that is acceptable to the computer. One type 403 data set is needed for each PABX trunk to the computer. Each push button phone has access to the computer via the PABX 24 hours per day, 7 days per week. The production worker who needs information accesses the computer data terminal by punching one or two digits comprising the inquiry transaction code on his push button phone. Receipt of a high pitched "data tone" from the computer indicates that the connection has been established. The data terminal equipment at the computer center then answers back with the word "Register" which may be a request to enter an 8 digit order control or register number of the job in question.

8.221 After receiving the register number, the computer quickly determines if this is a valid register number. If the computer finds the number is not valid, the data terminal equipment responds with the words "Re-dial Register." The computer will accept three attempts to enter a register number and if on the third attempt, finds that the number is still not valid, advises the user to "Request Aid" from his supervisor and ends the transaction.

8.222 When a valid register number is entered, the data terminal equipment voice response gives details concerning the last recorded move of the order between departments. The information may include the numbers of both the "from" and "to" departments, the manufacturing day and time of both release and receipt, quantity of parts on order, the scheduled completion date, and the part number. For example, in response to an order location and status inquiry, the voice response reply might be:

"From location 1010, date 081, time 1330, to location 1017, date 089, time 1715, quantity 10, completion date 093, part number 3A66025-IK."

The voice response may also provide the user with additional information. This may include a "Priority" classification code or a "Hold" code.

8.223 The voice-answerback system may also be used for collecting labor time and attendance data. For example, when an employee begins his shift, he goes directly to a pushbutton telephone and punches in his badge number. Again this number is automatically checked, and if it is a valid number, the computer answers back, "O.K."; if not, it responds, "Re-Dial Man Number." In addition, each time an employee starts work on a given parts order, he uses the pushbutton telephone to punch in a labor reporting code. The computer then verbally requests the employee's man number, labor classification code, department number, and order register number, signing off with "O.K." after all data has been properly entered.

8.224 A standard pushbutton pad with a 12-button layout is shown on Figure 5. As shown, each button has two frequencies, including

the "*" button and the "#" button. The caller may send 34 alphanumeric symbols from the 12 buttons. A standard telephone set with a 12 button pad is normally used in voice-answerback systems. A 16 button pad can be furnished on special request if required. Numbers are sent directly by pressing the numbered button while letters are sent by pressing the numbered button that has the letter to be sent, followed by pressing the "#" button one to three times depending upon the position of the letter on the button. For example, to send the letter "K" one would press the "5" button that shows "JKL" followed by pressing the "#" button twice.

8.225 The telephone set used with the voice-answerback computer installation may also be a regular rotary dial key telephone set plus a separately mounted push button dial pad.

8.226 Another telephone set that may be used is the pushbutton card dialer telephone. The card, in this case, may contain information on the part number, the use of the part, date due for production, etc.

8.227 The voice-answerback system operation is half-duplex on two wires.

The Western Electric 403D data set (or the equivalent) housing 1 to 16 type 403 receivers is used for multiple data set installations. The 403E receiver (or the equivalent) is a single unit model.

8.228 The computer answers inquiries by a voice vocabulary pre-recorded on a voice-answerback drum unit. In a typical system the drum surface is divided into fixed-length slots of time, and each of these contains one word. A series of magnetic heads are able to pick up the selected words under the control of the computer program. The word sounds are amplified and connected to the telephone line. Where a word occupies more than one slot on the drum, the computer will transmit the appropriate slots sequentially. The word vocabulary is limited by the size of the voice answerback drum. In a typical system the maximum number of words that can be used is 128. Most voice answerback systems use the ASCII code.

8.229 Both of the data systems previously described use standard push button telephone sets to generate the data input. This has the advantage of being inexpensive, but the number of input characters is severely limited by having only 12 buttons. Where a large number of characters must be used for the data input a more elaborate device such as a teletypewriter keyboard must be used. There are many different makes and designs of input/output devices which can be used to connect remote stations to a central computer center to handle customer's accounts. The computer is generally updated by the input/output machine at each remote station. These machines may be permanently connected to the computer on a private line leased from the telephone company or can be connected by a regular exchange line on the switchboard using a telephone dial to first establish the connection.

are not involved except to modulate and demodulate the data signal for transmission over the circuit.

		1

TABLE 1 - VOICE BANDWIDTH DATA CHANNEL AND C-TYPE CONDITIONING

)	I. Circuit Designation	3002 Channel	-	Conditioning	l ioning	Condi	C2 Conditioning	Condit	C4 Conditioning
	Use				Da	Data Only			
	II. General Characteristics	2-Point or Multipoint	ultipoint	2-Point or Multipoint	Multipoint	2-Point or	2-Point or Multipoint	2, 3 or 4 Points	ints
	Mode of Operation Method of Termination ImpedSource & Load Maximum. Signal Power	,		0-dBm for	Half-or Full Duple 2-Wire or 4-Wire 600-ohm-Resistive-B 0-dBm for Composite Data Signal.	Half-or Full Duplex 2-Wire or 4-Wire 600-ohm-Resistive-Bal. posite Data Signal.			
Š	III. Attenuation Char (Meas. betw. 600 ohm				16 dB ±	16 dB ± 1 @ 1000 Hz	łz		
	impedances at lineup) Expected Max. Var.	er.	9		Short- Long-t	Short-term ± 3 dB Long-term ± 4 dB			
	<u> </u>	Freq. Range	VardB	Freq. Range	VardB	Freq. Range	VardB	Freq. Range	VardB
	(Ref. 1000 Hz)	300-3000 500-2500	-3 to + 12 -2 to + 8	* 300-2700 *1000-2400 2700-3000	-2 to + 6 -1 to + 3 -3 to + 12	*300-3000 *500-2800	-2 to + 6 -1 to + 3	*300-3200 *500-3000	-2 to + 6 -2 to + 3
	Frequency Error					± 5 Hz			
	IV. Delay Charactenistics Absolute delay				No	Not Specified			
		Freq. Range	μ Sec.	Freq. Range	μ Sec.	Freq. Range	μ Sec.	Freq. Range	μ Sec.
	Env. delay distortion	800-2600	<1750	*1000-2400	<1000	*1000-2600	< 500	*1000-2600	< 300
	AA AG II			800-2600	<1750	* 600-2600 * 500-2800	<1500 <3000	* 800-2800 * 690-3000 * 500-3000	< 500 <1500 <3000
	V. Noise Characteristics Message Circuit Noise			0	0-50 Miles	- 31 dBrnc	บต		
	Impulse Noise				5 counts in	15 counts in 15 minutes @ 72 dBrncO	72 dBrncO		

These specifications are covered by Interstate Tariff FCC No. 260 (1/1/69).

All others are the current administrative instructions of A.T.& T. Co.





FIGURE 1







Fig. 3 ACOUSTICALLY COUPLED ANALOG DATA MODEM FUNCTIONAL DIAGRAM



FACTORY DATA SYSTEM FIGURE 4

PUSH BUTTON DIAL CHARACTERS AND FREQUENCIES




FIGURE 5

- This appendix covers a brief summary of terminology definitions commonly used in data communications.
- ALPHANUMERIC (1) A contraction of alphabetic-numeric; (2) pertaining to a character set that contains both letters and numerals and usually special characters.
- AMPLITUDE MODULATION (AM) A form of modulation in which the amplitude of the carrier is varied in accordance with the amplitude of the original information signal.
- AMPLITUDE SHIFT KEYING (ASK) A form of modulation in data communications where the amplitude of an audio carrier is shifted between two discrete levels by the digital signal to represent a mark (binary "l") or a space (binary "o").
- ANALOG Pertaining to data in the form of continuously variable physical quantities. Contrasts with Digital.
- ANSWER-BACK A signal transmitted by the receiving device back to the sending device to indicate that the receiver is ready to accept or acknowledge the receipt of data.
- ASCII American Standard Code for Information Interchange.
- ASYNCHRONOUS TRANSMISSION Transmission in which each information character or sometimes each word or small block is individually synchronized, usually by the use of start and stop elements. The gap between each character (or word) is not of a necessarily fixed length. Asynchronous transmission is also called "start-stop transmission."
- AUDIO RESPONSE A system of generating an audible, verbal output from a machine.
- BAUD Unit of signaling speed. The speed in bauds is the number of discrete conditions or signal events per second. (This is applied only to the actual signals on a communication line.) If each signal event represents only one bit condition, baud is the same as bits per second. When each signal event represents other than one bit, (e.g. see Dibit) baud does not equal bits per second.
- BAUDOT CODE Referred to as "5-bit code," this is a system for encoding symbols in printing telegraphy.
- BINARY A code that uses information that has only two distinct states, e.g., on-off, mark-space, yes-no, 1-0.

and the first of the name of the state of th

REA TE & CM 760 Appendix I

BIT - (1) An abbreviation of binary digit. (2) A signal character in a binary number. (3) A signal pulse in a group of pulses. (4) A bit represents the choice between a mark of space (one or zero) condition.

- BIT-SERIAL The form of information transfer where each bit is transmitted sequentially.
- BUFFER (1) A storage device used to compensate for a difference in rate of flow of data or time of occurrence of events when data is transmitted from one device to another.
- BUSINESS MACHINE Office machine equipment normally owned by the customer and used in business offices for storing and/or processing data. It may or may not be a part of a communication system.
- BYTE A group of binary digits which is the smallest addressable unit of information in a memory.
- CHARACTER The actual or coded representation of a digit, letter, or special symbol. One symbol of a set of elementary symbols such as those corresponding to the keys on a typewriter. The symbols usually include the decimal digits 0 to 9, the letters A to Z, punctuation marks, operation symbols, etc.
- CIRCUIT, MULTIPOINT A system consisting of a circuit connecting three or more terminals, any or all of which may simultaneously receive information.
- CODE A system of symbols for meaningful communication, such as representing data or instructions to a computer.
- COMMON LANGUAGE A machine sensible information representation which is common to a related group of data processing machines.
- COMPUTER A device capable of accepting information, applying prescribed processes to the information and supplying the results of these processes. It usually consists of input and output devices, memory storage, arithmetic, logic, and control units.
- CONDITIONING, LINE Actions taken and/or equipments provided to correct circuit distortion levels, or impedances to established standards.
- CONNECTING ARRANGEMENT Equipment provided by the telephone company which is interposed between customer-provided facilities and facilities of the telephone company to protect the telephone network.
- DATA COMMUNICATION " The transmission of information to and from data processing equipment. This includes selection, assembly, sequencing, and routing of data at one point and transmission of the data in a prescribed mode and format to a remote point or points for processing. It also includes the distribution of processed data from a computer or other processor to remote terminals or other data processing equipment.

- DATA SET A device which converts the signals from a business machine to signals that are suitable for transmission over communication lines. It also converts signals from communication lines to signals suitable for a business machine. Performs related functions.
- DATA TRANSMISSION The sending of data from one part of a system to another.
- DECODE To determine the meaning of individual characters or groups of characters in a message through the reversal of some previous coding.
- DEDICATED Permanently assigned. In data transmission it usually refers to leased or private communication lines or equipment.
- DEMODULATION The reverse of modulation. The process of retrieving the original signal from the communication channel.
- DIBIT A group of two bits. In four-phase modulation each possible dibit is encoded as one of four unique carrier phase shifts. The four possible states for a dibit are 00, 01, 10, and 11.
- DIGIT CHECK A redundant digit (or digits) carried within a unit item of information (character, word, block, etc.,) which provides information about the other digits in the unit in such a manner that if an error occurs the check fails.
- DIGITAL Information expressed as a sequence of discrete elements. Pertaining to data in the form of digits.
- DIRECT ELECTRICAL CONNECTION Denotes a physical connection of the electrical conductors in the communications path.
- DOWN-TIME The period during which a computer or other data equipment is malfunctioning or not operating correctly due to mechanical or electronic failure as opposed to available time, idle time, or stand by time, during which the computer is functional.
- DUPLEX OPERATION Full-duplex operation provides for transmission of data in two directions simultaneously. Half-duplex operation allows two-way transmission, but in only one direction at a time.
- DUOBINARY- A coding system that makes possible a doubling of transmission speed over a communication channel. Duobinary coding techniques permit detection of errors without the addition of error-checking bits to characters.
- EDP Electronic Data Processing.
- ERROR An occurrence during transmission such that different information is received than was transmitted; a mistake.
- ERROR-CORRECTION A system that automatically detects and corrects errors.

REA TE & CM 760 Appendix I

ERROR-DETECTION - A system that automatically detects and identifies errors.

- ERROR RATE The probability of an error occurring during the transmission of a message. Error rates of 10-5 (one error in 100,000 bits) are typi-
- FREQUENCY MODULATION(FM) A form of modulation in which the frequency of the transmitted signal is varied in accordance with the information being transmitted.
- FREQUENCY SHIFT KEYING (FSK) A form of modulation in data communications where an audio carrier is shifted between two discrete frequencies by the digital signal to represent a mark (binary "l") or a space (binary "o").
- HALF-DUPLEX See Duplex

- HARD COPY A tangible, printed copy of data information.
- HARDWARE The equipment that comprises a data processing system. It is most frequently used to differentiate between the physical features of the system and those which the user introduces through coding and programming.
- IMPULSE NOISE Any burst of high amplitude closely spaced impulses, followed by a relatively quiet period. The objectives for impulse noise limits are stated in the number of counts (bursts) above a given thresh-. old. An average impulse rate of 1.5 counts per minute results in an error rate of 10-5. The impulse noise rate is determined by using commercially available impulse noise counters. Improvements in the signalto-impulse noise ratio can be obtained by shortening the repeater spacing near the central office.
- INFORMATION CHANNEL The transmission and intervening equipment involved in the transfer of information in a given direction between the two terminals.
- INPUT The information fed into a computer system, data to be processed, the device or devices used to bring data into another device.
- INPUT/OUTPUT A general term for the equipment and the data involved in a communication system.
- INTERCHANGE CIRCUIT A circuit between the data terminal equipment and the data communication equipment for the purpose of exchanging data, control, or timing signals.
- INTERFACE The point of connection between the business machine equipment and the communications channel; a common boundary between the two parts. This is where the customer's equipment and the data set meet. Compatibility is essential; the data set must be able to accept the output signal of the customer's equipment and vice versa. 100 grant to the second of the

- JITTER See Phase Jitter
- LEASED LINE A facility reserved for sole use of a single leasing customer
- MEMORY A general term for equipment that holds or stores data in electrical or magnetic form.
- MESSAGE A group of words, variable in length, transported as a unit. In telegraphic and data communications a message may be composed of three parts.
 - 1. A heading, containing a suitable indicator of the beginning of the specific message, together with information on any or all of the following: The source and destination, date and time of filing, and routing or other transmission.
 - 2. A body containing the information to be communicated.
 - 3. An ending containing a suitable indicator of the conclusion of the specific message, either explicit or implicit.
- MESSAGE ROUTING The function performed at a central message processor of selecting the route, or alternate route if required, by which a message will proceed to the next point in reaching its destination.
- MODE Method of operation.
- MODEM A contraction of modulator-demodulator used to describe equipment containing both.
- MODULATION The process in which a signal suitable for transmission over the communication medium is altered in a definite pattern in accordance with the information being transmitted.
- NETWORK CONTROL SIGNALING UNIT Denotes the terminal equipment to provide for network control signaling. Usually a dial on a telephone set.
- OFF-LINE Implies no direct connection between the communication line and the computer system or equipment.
- ON-LINE Implies a direct connection between the communication line and the computer system.
- OUTPUT The results of computer calculation or operations that are conveyed to peripheral devices such as printers.
- PARALLEL OPERATION A method of transferring information in which all parts of a character (or message) are handled simultaneously. A parallel data set accepts and transmits an entire character at once. A MARKET TO SANT TO

REA TE & CM 760 Appendix I

PARITY CHECK - A means of detecting errors in received data. Binary "ones" are added to the transmitted character so that the total number of binary "ones" is always odd or always even. At the receiving end, the sum is rechecked to determine if it is still odd or even.

- PERIPHERAL EQUIPMENT Equipment that works in conjunction with a computer but is not part of the computer itself, e.g., card punches and readers.
- PHASE JITTER A form of distortion in which the transmitted signal is phase modulated by noise. The effective noise occurs in the bandwidth from 0 to 300 Hz and typically occurs at the ringing and powerline frequencies and their harmonic frequencies. The 120 Hz component is often the dominant component. Phase jitter also appears as bursts of noise commonly referred to as phase hits. Principal sources of phase jitter are frequency division multiplex equipment and to a lesser degree automatic equalizer and associated equipment. At data rates of 3600 bps and above phase jitte may have a significant effect. Proper data set design can minimize the effect of phase jitter. The term "phase jitter" is usually used in analog data transmission. (See also Timing Jitter)
- PHASE MODULATION (PM) A form of angle modulation where the instantaneous phase of the carrier signal is varied in accordance with the information signal.
- PHASE SHIFT KEYING (PSK) A form of modulation in data communications where the instantaneous phase of an audio carrier is shifted between two discrete values by the digital signal to represent a mark (binary "1") or a space (binary "0").
- POLLING A technique used for collecting and disseminating data between a central processor (computer) and a number of remote stations. The computer is programmed to originate a request for data to each remote station in sequence, or requests each remote station to put itself in a condition to receive data.
- PRIVATE LINE Denotes the channel and channel equipment furnished to a customer as a unit for his exclusive use without interchange switching arrangements.
- PROGRAM As a noun, it means a list of instructions to be followed by a computer. As a verb, it means to prepare a program, the complete sequence of machine instructions and routines necessary to solve a problem.
- PULSE A signal of short duration generally characterized by a sharp rise and decay time of a quantity whose value is normally constant.
- PULSE CODE MODULATION (PCM) The process of converting an analog signal to a digital code.

- QUEUING To hold calls for an operator then to present them to the operator sequentially in the order received.
- READOUT The display of the output of a computer.
- REAL TIME A data processing system that analyzes and processes input data as soon as it is generated.
- REMOTE Input/Output equipment which is physically separated from the computer by a considerable distance.
- REVERSE CHANNEL A channel which provides a means of signaling or communicating in the reverse direction. This is intended for use in systems where error checking or monitoring is desired.
- REDUNDANCY CHECK An automatic or programmed check based on the systematic insertion of components or characters used especially for error checking purposes.
- SERIAL-PARALLEL A combination of serial and parallel; e.g., serial by character parallel by bit, descriptive of a device which converts a serial input into a parallel output.
- SERIAL TRANSMISSION A system of transmitting the bits of a character on the line in sequence, generally used in telegraphic operations. A serial data set handles only one bit at a time.
- SOFTWARE Paperwork, procedures, and other non-equipment items necessary for a data system. All programs and routines used to extend the capabilities of computers such as compilers, routines, etc.
- SPEED OF TRANSMISSION The rate at which data is sent over a transmission facility expressed as the average rate over some significant time interval. The quantity is usually expressed as average characters per second or average bits per second.
- STORAGE The portion of a data processing system that records, holds, and allows access to information.
- SYNCHRONOUS Pertaining to two or more machines operating in the same period and phase.
- TERMINAL A point in a system or communication network at which data can either enter or leave; an input/output device capable of transmitting entries to and obtaining output from the system of which it is a part.
- TIMING JITTER A term used in digital transmission for distortion caused by random phase modulation which is introduced at each repeater cumulatively. Sources of timing jitter include inter symbol interference, finite pulse width, clock threshold offsets, and timing degradation. (See Phase Jitter).

REA TE & CM 760 Appendix I

VESTIGIAL SIDEBAND - A type of amplitude modulation where a prescribed portion of one side band is suppressed, VSB is used on high speed data modems - 3600 bps and above.

- VOICE-ANSWERBACK A computer system whereby a computer answers inquiries by a voice vocabulary pre-recorded on a voice-answerback drum unit.
- WORD In computing, a sequence of bits or characters treated as a unit and capable of being stored in one computer location; ordered set of characters, normally digital, which is the normal unit in which information may be stored, transmitted, or operated upon within a computer.

QUICK REFERENCE TO BELL SYSTEM DATA SETS



DATA SET	TRANS (T) NEC (R)	HAX SPEED (bits/sec)	SERVICE: DIAL PRIVATE	PRINCIPAL USE
Yelceband;	digital-serial (100 & 200 Series)		
103A 103E 103F 103H 113A 113B 201A 201B 202C 202C 202C 202C 202C 203A 102B 203C 203C	T-R T-R orig & ans T-R T-R orig T-R ans T-R	300 300 300 300 300 300 300 2000 2400 1200/1600 1800 3600/7200 3600/7200 4800	000 & PL 000 & PL 000 & PL 000 & PL 000 & PL 000 & PL 000 & PL 000/PL 000/PL 000/PL 000/PL 000/PL 000/PL 000/PL 000/PL 000/PL	ITY, low-speed, binary, non-clocked device Multi arr, cab mtd, for low-sp times-shared com ports term ITY, low-sp binary, non-clocked devices Built-in ver 103G for Use/W #37 TTY or custom mach ITY, low speed binary, non-clocked devices Hulti arr, cab mtd for low sp time-shared com ports term Hed Speed mach binary, sync devices Hed ap mach binary, sync devices Hed ap mach binary, sync dev on multi-pt layouts Hed binary non-sync devices Hed binary non-sync devices Hed binary non-sync devices Low cost, med speed, binary non-sync trans device Hed speed, binary, sync device
401A	Y		000 & PL	followsky San and an area of the san area.
401E 401H 401J 401L 402C 402D 403D 403E	TTRTTRR	90 130 130 130 600 600 40 40	000 å PL 000 å PL 000 å PL 000 å PL 000 å PL 000 å PL	Low-cost, low speed, non-sync dev with 24 character req Low-cost, low speed, non-sync dev with 99 char, att. open Remote, non-sync, telemetry dev Low 3p non-sync data col center dev serv remote term Alarm reporting terminal equipment Tape sending device to channels binary date Tape receiving dev to channels binary data Receiver for multi data set collec or audio resp system Individual receiver for sm data collec or audio resp sys
Yolcebend:	analog (600 Sari	141)		successful received for sin water collect of audio resp sys
602C 603A 603B 603D	Y+R Y R Y	* *	000 & PL 000 & PL 000 & PL 000	Fax or talemetry sending or rec dev w one ch or info 0-1000HZ Fixed EKA sending dev with 1 ch of into, 0-100HZ Fixed EKA receiving dev with 1 ch of info, 0-100HZ
Widebands	digital-serial (100 Series)		
3018 3036 3030	T-R T-R T-R T-R	40,800 19,200 80,000 230,400	PL PL DATA-PHONE SO PL PL	High-sp, binary, sync bus mach or 2-lev hi sp fax dev High-sp, binary, sync or non-sync business mach High-sp, binary sync bus mach or 2-lev hi-sp fax dev High-sp, binary, sync bus mach
TYPE			YOTCEBAHD DATA	ACCESS ARRAMGEMENTS
Manual Autometic Autometic	S R S R S R		000 000 000	Ac analog device Dev employing contact closures for control leads Dev employing ElA RS 2328 interface
TYPE	AUTOMATIC CALL		DATA AVXILIA	AY SETS
801A 801C	Rotary Dial TOUCH-TONE DIAL	04 514 103A/E/Q/ 04 514 103A/E/Q/	ACOS, D\0205, A [05, H ACOS, D\0205, A [05, H HTHOH DYAHIXOR99A	(B/C,401),402C/0,403E&602C B/C,401),402C/0,403E&602C LY_RATES
DATA DATA- SET PIKKE SERYI	SYC	REMARKS		DATA DATA- PL REMARKS SET PHONE SYC SERVICE
103A \$ 25 103E \$ 21 103F 103H \$ 35 113A \$ 10 113B \$ 11	S 20 Cabinat,	equipment 175/mo, (401H \$ 9 \$ 11 401 \$ 40 \$ 40 Yofce answerback \$5/mo extra. 401L \$ 20 Rate for 401L1, 401L2 is \$25/mo. 402C \$ 20 \$ 24 Rev ch \$5/mo extra. Unattended ann \$5/mo extra. 4020 \$ 60 \$ 53 Rev ch \$5/mo extra. Unattended ann \$5/mo extra. 4030 \$ 37 Rate for Interface (1)8(2) Cabinet, con equip \$75/mo
1138 \$ 11 201A \$ 70 201B 202C \$ 35 202C \$ 14	\$ 72 \$ 30 Reverse C \$ 14 Mates for	hannel \$5/mg, extra 20269 Sets 202 []	joses' soses	403E \$ 53 Rate for interface (1)&(2). extra- 602C \$ 30 \$ 28 Reverse channel \$5/mo extra- 603A \$ 12 \$ 16 603B \$ 12
2028 1 20 203 A-B-C	\$ 25 Hanual or	ig and 112 respectivity. Up to 8 sets 52 Mepending on featur	/mb. extra.	801A \$ 25 Answer detection \$5/mo extra. 801C \$ 25 Answer detection \$5/mo extra.
708A \$115 3018	\$115 \$425 Part of w	ildeband terminal.		DATA ACCESS ARRANGEMENTS
3030 \$275	operation \$425 Part of v (1ync) A Phone SO	rideband terminal. R i, Hon-sync \$65/#0. rideband terminal ur part of station ter (sync or non-sync).	extra. ider PL offerings minal under Data- . Non-sync for PL	Hanual 2 Auto 8 6 Control lead signals conform to EIA %3 2328 Contact clo used for cont leads without power prov by Telco Auto 3 5.50 Contact clo used for cont leads with power prov by Telco
3030	\$65/ne. 6 \$650 Part of v \$65/ne. 6	atra. Ideband terminal (s	ync). Hon-sync	Appendix II

MITELEPHONE ENGINEER & MANAGEMENT, JANUARY 1, 1973

Buyer's Guide to Data Modems and Acoustic Couplers

		DUSTIC		SE Q	SHEET THE	ដ្ឋ	8 011	> u	¥÷	5		9	:
	50	MODIFICATION CONTRACTOR	SPEED- NEW YMAX	MOULATION STRCK-ASTRCK	CHANNEL	MAIS/MINIS	BUILT-IN EQUALIZATION	MOUNTING/ DEH CAND AYAILABLE	Unches)	COMPATIBLE W/BELL	PRICE	BITS/SECOND /DOLLAR	FEATURES
	YTC-1 YTC-2 AHT-1 AHT-2	A A H H	300 Hax 300 Hax 300 Hax 300 Hax	FH-S FH-S FH-S FH-S	Voice Voice Voice Voice	HD4FD	No No No No	Cab-NO Cab-NO Cab-No Cab-No	10x10x5 10x10x5 10x10x5 10x10x5	101A & 102F & 113			Orig Only Orig & Ans Orig Unattend Orig & Ans
merican Data Systems 851 Mason Ava anoos Park, Ca. 13-882-0020	403/2 448/1V 412 424	H H H	0/300 2400/4800 0/1200 1200/2400	FM-ASYNO DSSC-PH & AM-SYN FM 5/A PM-S	Yolca	FD - 4W HD - 2W	Auto- Adaptive Compromise or Auto	Desk Cab or 3 cards 1 card 2 cards	4x10x12 4x10x12 8x10 6x9 6x9	103 Ho 2020 2018	\$ 400 \$ 2400 430 800	.75 .06 2.8 3.0	Uses HOS-651 Reverse 150 8 Channel (Enclosure)
nderson Jacobson 065 Horse Ave. unnyvale Ca.	ADA6- 1200/1210 DCH150 AUC-300	A/H	0/1200 0/150 0/300	FH-A FH-A	Yoice 5 mi tel cabl	HO HO	Aa No	Cab-No Cab-No	45x105x11 7x11x25			\$.43	For Short private conn
06-734-4020 strocom Corp. 93 Commercial t. Paul. Kinn, 12-227-8991	110/130 112 320/324	H/A A B	0/300 0/1200 2000/2400	FH-A FH-A PH-S	Yolce Yolce 320 Voice 324 C-2	FO HO HD/FO	Ho Ho Optional Compro	Cab-Yes Cab-Yes Cab- Rack-Yes	3x11x10 4x12x14 75x11510	103 202 201		2.00	Walnut Cab.
	120 \$C200 400	н н н	2400/4800 0/1800 2000/9600 10K/100K	PH-A PH-S PH-S PH-S	Yolce Aby 14000-2 Private Private	FO-4W HD/FO HD/FO HD/FD	Han or Adaptive Compro No No	Cab,Ra,Y Cab,Ra,Y	74x184161 3x11x10 3x11x10 74x114x10	202 No	\$ 830 1825];} 5.5 -	Limited Distance Limited Distance
owmar/All, Inc. cton, Mass.	6103A 6000A	н н	0/300 1200/2400	FH-A PH-5	Voice Voice	HO/FD	Ho Yes	Cab. Yes Cab. Yes	4x134x12 4x94	103 No	\$ 645 \$ 1250	.47 1,92	
erterfone ommunications	05103A H0132	ii B	0/440 0/300-440	FH-A	Yoice Yoice	HO/FO HO/FO	Na No	In TTY Cab,Ra,Y Card Cag	14x17x2	103 1016 103E	\$ 550 \$.60	Auto Ans Self Test TTL Interface Available
odes Corp.	4800	Н.	3200/4600	QAH-S	Yolce	FD/4D	Auto Dig.	Rack, Cab	19x7x20%		\$5575		Mil 188 Interface Avail
5 Riverdale Ave ewton, Mass, 17-969-0600	7200 9600 4000Hultlp	H H L II	4800/7200 4800/9600 4800	2-M40 2-M40 2-M40	Yoice Yoice Yo Hultipt Polled	FD/4D FD/4D FD/4D	Adaptive	(9 cards	19x7x204 19x7x204 19x7x204	No	8000 11,500 5575	.90 .83 .86	Equalizer Updates 2400 times per second 50 MSEC Equalization
	4800Dia1	н	4000	QAH-S	Switch-Yol	FD/40		•	19x7x204		5975 \$ 700	.80	Auto-Answer
ollini Radio Co Hemport Beach Ca 14-833-0600	.THX202C .THX202E TE-236	и И	0/150 0/300 1200 or 2400	FR-A FII-A DCPSK-s	Va (10Ch) Va (5Ch) Voice	HD/FD HD/FD HD/FD	Ho Ha Yes	Ra, Cab, Y	(2 Ch)	No	1117	to 1.27	
om Data Corp. 544 W. Dakton flet, Jil.	201F4-13	К	0/300	FM-A	Yolce	FD FD	No No	Cab-Yes Cab-Yes	12x4x6 Card4410 12x4x6	101C 103/113	\$ 425 245	\$.75 1.22	Up to 14 Channels/Yolco RS-232/TTY
12-692-6107	302A2-13 30202-13 302F2-13 330F2-13 330F2-13 30202-43 301P2-11 310 320 450F2-13 150A2-11	**************************************	0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/350	FH-A FH-A FH-A FH-A FH-A FH-A FH-A FH-A	Yoice Yoice Yoice Yoice Yoice Yoice Yoice Yoice Yoice Yoice Yoice	FD F	Ho Ha Ha Ha Ha Ho Ho Ho Ha Ha Ha	Cab-Yes Cab-Yes Card Card Cab-Yes Cab-Yes Xit Card Card Card Cab-Yes Cab-Yes	12x4x6 12x4x6. 4\x13\x 4\x13\x 12x4x6 12x4x6 12x4x6 4x5 4\x10\x 4\x10\x 4\x10\x	Ho 103/11:	265 249 195 175 295 325 245 125 150 395 147	1.13 1.22 1.55 1.02 .93 .22 2.40 2.00 ,76	RS-232/TTY RS-232/TTY CBI/CBS Private line CDI/Private line CBI/CBS Fits Teletype O.E.H. O.E.H.
Communications Lagic, Inc. 1400 Vestpark Suite 355 Houston, Yex. 713-785-8100	L-2400 L300A-14 L3003-14 L300C-14 L300C-14 L300E-14 L300F-14 L1800	HAAH	2400 Hax 0/300 0/300 0/300 0/300 0/300 0/300 0/300	PH-S FH-A FH-A FH-A FH-A FH-A FH-A	Priv-C2 Yotce Yotce Yotce Yotce Yotce Yotce	FD/HD/FD HD/FD HD/FD HD/FD HD/FD HD/FD HD/FD	No No	Cab-Yes Cab-No Cab-No Cab-No Card Cab-Yes Card Cab-Yes	10x11x1; 4x1 6x8 6x8 10x11x1; 6x8		795 190 210 190 110 230 150 350 525	5.14	1-Orig Only/2-Rec Only Auto Answer Auto Answer Rev-Chan, Auto Answer
Computer Trans- mission Corp.	911	H	0/1800A 240J/94005	PCH-S	Wire Prs	FO/HO	М	Cab	45x16x1		\$1850		
1352 Utah Ave. 11 Segundo, Ca. 113-973-2222	915 916	H	kbps-20kbps 20kbps to 250kbps	PCH-S PCH-S	Wire fre	FD/HD FD/HD	M	Cab	:	No No	1850 1950		
	917 1013	H	250kbps to 1mbps 0/1800A 2400/4800/	POI-S POI-S	Infrared Pairs	FD/HD		Cab	eptical Skl2x19		2200 2950		
	1815 1816 1817 900	H	9600kbps S Te 20kbps 20/250kbps 250/1mbps	PO1-5 PO1-5 PO1-5	:	FD/HD FD/HD FD/HD	MA MA	Cab Cab	45x16x1	2 No No No 22	2950 3300 3700 1300		
ş.	900 931 935 936 937 1831 1835 836 837	*******			pire fairs		NA NA NA NA NA NA		7 3/4x1	O's No No No No No No No	1150 1150 1250 1500 2400 2400 2650 3050		ontinued on next pay

Appendix III

Buyer's Guide to Data Modems and Acoustic Couplers

Continued

	MODEL.	MODER/ACQUISTIC: COUPLER	SPEED- HIM/MAX	MODILATION STRCH-ASTRON	CHANNEL	DUPLEX/SIMPLEX	BULT-1N EQUALIZATION	HOUNTING/ OEN CARD AVAILABLE	OTHENSTONS (Inches)	COPATIBLE W/BELL	PRICE	BITS/SECOND /DOLLAR	FEATURES
Data Access Systems, Inc Mountain Lks, Ad		H H/A H/A	50/300 10/300 10/300	FH-A FH-A FM-A	Voice Voice Voice	FD/HD FD/HD FD/HO	řio Ho Ho	Cab-Ho Cab-Ho Cab-Ho	5x9x4 7x9x3	103A 103A 103A	\$ 295 295 400	\$1.02 1.02 1.20	Ans Only Set Available Desk Coupler Auto Answer
Catasery Burlingame, Ca	1310 1340	Н	0/30 0 0/300	Dt-A Dt-A	Yoice Yoice	FD FO	No No	Card Cab	415x6 13x61x215	103A/103I	E \$195 E \$75	1.54 .52	Improved Fault locating All Digital Integrated
Digital Tach- niques, Corp Royal Cak, Hich	2161 .3300	Å	0/300 0/150	A-KS A-KS	Yoice Voice	HD/FD	Ho No	C4b 33/35TTY		103 103	295 290	1,02 .51	
ESE Ltd. 1780 Albion Rd. Rexdale, Ontario		н	4800Hax	QAM-S	Varies	HO/FD	Kan or Auto Adapt	Cab,Rack Yes	184x8x17	Но	4600- 5900	,80- 1.01	Can be up-graded
General Data Comm. Industrie 637 Newtown Marwalk, Conn. 203-847-2445			0/300 0/1200 0/1200 0/1200 0/1200 0/1200 0/1200 0/2000	## ## ## ## ## ## ## ## ## ## ## ## ##	Voice Voice Voice Voice Voice Voice Voice Voice Voice Ivate Line Ice-PL Ice-P	HD/FD HD/FO HO/FO SX SX SX SX SX SX	No N	Cab-Yes	12459.23 124	103A, EJ 11 103A, F, G 103A, F, G 103A, F, G 103A 103F 103F 103F 103F 103F 103F 103F 103F	H 450	*AOTE: All prices are for 3-19 unit quantities.	Analoop Test Analoop/Dataloop Analoop Analoop/ Analoop/Bataloop Analoop/BC Loopback Analoop/DC Loopback Analoop/CC Loopback A
General Electric Communication Systems Business Div. Hountain Yiew Jachburg, Ya. 703-846-7311	:TOH-110 TOH-210 TOH-211 TOH-211 TOH-211 TOH-115813/6 TOH-130 Olg/Net 150 Og't 160 Og't 500 Og't 500 Og't 7201	H H H A A A A A A B B B B B B B B B B B	0/300 0/300 0/1800 0/1800 0/300 0/300 10,150,300 0/600 to 50,000 to 50,000 to 300 BPS	FH-A YOFH-A YOFH-A YOFH-A YOFH-A YOFH-A POCH PROCEED FOR A-FSK SIGNATURE FOR A-FSK SIG	ice ivate ivate ivate	FO FO/HO FO/HO FO FO/HO FO FD FD FD FD FD	Ho Na Yes Yes No Na Ha	Cab Cab Cab Cab Cab Cab Cab Cab,Rack Cab,Rack Cab,Rack Cab,Rack Cab,Rack Cab,Rack Cab,Rack Cab,Rack	6x13 3/4c 6x13 3/4e 4x84x10 4x84x10		C	XIQ S N	Private or DAA Switched Met • (63 has 20 ma TTP conn ns Short Length als per line
IE Automatic Hectric Horthlake, III.	AETOJA AMTOJE	н	0/300 0/300		ice ivate	H9/F0 H0/F0	No No	Cab Cab	8x154x64 8x154x64	103A 103F	\$ 580 535	\$.5£ .55	
GTE Lenkurt Inc. 1105 County Rd. San Carlos, Ca. 415-491-8461	25C 250 26C 26C 26C-40,8	H H H	75/600 75/200 1200/2400 4800Hax 23,400/ 40,800	fil-A fM-A Cuobin- ary fM SS Cob A/ Luobin- ary fM-S fil-A	Yoice Yoice Yoice S C2 Wide- band Yoice	HD/FO/S		Cab.Ra.II	6x6x15				Hultich18075b/s-1r50Ub/ Multich25975b/s-70200b/ 0/1800b/s A 150/24U0b/s
1.0.M. White Plains, MY	3872 3875	н	1200/2400 1600/7200	PH	Voice Voice-CZ	HO/FO	Auto Adjust	Cab Cab		Na No	\$2975 8400	\$.8] .85	Pt to multipt-switch ne is speed backup
I.I. Communica- tions Corp. IIIlow Grove.Pa	113 201A/B	и и и	0/300 2600/2400 2400	FII-A PII-S PII-S	Yolce Yolce Yolce	FD/HD FD/HD	No Adapt, Adapt.	Cab,Ra,Y	5x5 10x10 10x10	113/103 2014/B 2018	\$ 800 700	\$ 3.0	, , , , , , , , , , , , , , , , , , , ,
ITT Data Equip. å Systems Dis E. Hutherford,%	f	н	2400Hax	PH-S	Yoice 1800-62 2400-64	FD/HG	Compro	Cab,Ra,N	6x16'jx13 4 3/4x17'j		\$1430	\$ 1.7	

^{32 |} TELEPHONE ENGINEER & MANAGEMENT, JANUARY 1, 1973

į

Appendix III

Buyer's Guide to Data Modems and Acoustic Couplers Continued

	MODEL	MODEN/ACOUSTIC COUPLER	SPEED- HIVME	STICH-ASTICK	CONDITIONING CONDITIONING	DUPLEX/SIMPLEX	BUILT-IN EQUALIZATION	MOUNTING/ GEN CARD AVAILABLE	DIMENSIONS (Inches)	COMPATIBLE W/BELL	PRICE	/DOLLAR	FEATURES
Phonplex Corp. Huntington, N.Y.	DVK-1300	К	-0/1300			HO/FO							Combined Vo & Dat Tran
Prentice Elect- renics Corp. 198 San Antonio Pala Alto, Ca. 415-337-0490	OC-22 P103A PLOA1 PLOA2 PLLA 202 PSLA P-202 P-LRA-LU	AH H H H H H H H H H H H H H H H H H H	0/300 0/300 0/150 0/150 0/150 0/1200 0/150 0/1240 600/19,200	FH-A FH-A FH-A FH-A FH-A FH-A FH-A SANC	Voice Voice 4 mi Pr 8 mi Pr Voice Voice Voice Voice Voice Voice Twisted Pr	HD/FO HD/FO HD/FO HD/FO HD/FO HD/FO HD/FO HD/FO H/F	Ho Ho Ka Ho Ho Ho Ho	Cab Cab,Ra,Y Rack,Ca Rack,Ca Rack,Ca Rack,Ca Rack,Ca Rack,Ca St.Alone	4x74 4x74 4x74 4x74 4x74 4x4x74	103 103-1138 (184) (184) (184) 202C/D (184) Bell	\$298 180-215 110-135 115-140 130-160 320/360 160-195 350 800	1.37 1.3 4.6 3.75	Also Inductive Auto Ans. Short As. Short As. Leased Line Adpt. 4 Channels/Pair
Pulsa Communi- cations, Inc. P.O. Box 1225 Alexandria, Va. 703-820-0652	4081 4082 4082-9 4083 4084 4085 4086	H H H	0/300 0/300 0/300 0/300 0/300 0/300 0/300	FH-A FH-A FH-A FH-A FH-A FH-A	Voice Voice Voice Voice Voice Voice	HD/FD HD/FD HD/FO HD/FO HD/FO HD/FD HD/FD	No Ho Ho Ho Ho Ho			10GA/C 10GA/C 113A/B 103F/S 103E/113B 103A2 113A			Autiple Sot Rack Mt. Stand Alone Multiple Set Multiple Set Stand Alone Stand Alone Orig Only
Ovindar Electronics, Inc 60 Faden Ad. Springfield, H.J	QD1-202/60	н н н	0/300 0/300 0/1800 0/(2)1200	A-KA FH-A FH-A QAH-A	Valce Valce Va-1200 C2-1800 Va-C24H	HO/FO HD/FD HD/FD/S FD/S	Adj 180	Cab, Yes O	194275x41	No 202	\$765 660 800		Looping Back Loop, Back, Freq Max Loop Back
Rixon Inc., A Subsidiary of Sangamo 2120 Industrial Pkwy. Silver Spr., I'd. 20904 301-622-2121	TIOIC TO 3A 4 TIO3F2 TII3A TII3AS TII3ATS TII3BOS	N H H H H H	0/200 0/300 0/300 0/300 0/300 0/300 0/300	FH-A FH-A FH-A FH-A FH-A FH-A	Yolce Yolce Yolce Yolce Yolce Yolce Yolce	FO FO FO FO FD	No No No No No No	Cab Cab Cab Cab Cab Cab	95x94 11x114x4 11x114x4 10x104x3 6x124x34 6x124x34 30x27x22	113A 113A 113A 113A 113B	\$ 615 520 480 265 205 195 800 + 320/ch/	\$.32 .57 .62 1,13 1,46 1,53 .93	Use in TTY Only Can Contain 20 C1138 Cards
	DS-1800B/C T202C T202D T202E TA201A3/4E TA20183/4E DS-2400 TA201A/B3/- DS-2401 T4800F	# H H H K K H H K K H H K K H H K K K H H K K K H H K K K H K K K H K K K H K K K H K	0/1800 0/1800 0/1800 0/1700 2000 2400 1200/2400 2000/2400 2400 4800	FH-A FH-A FM-A PHASE-S PH-S PHASE-S PH-S PHASE	Voice-C Voice-C C-2 Con	FD 1 FD/4H d- FD	Strap- pable Compro Compro Compro Compro Strap- Compro Strap- Adj Delay	Cab, Raci Cab, Raci Cab Cab, Raci Cab, Raci Rack Cab, Rac	f 9x13x4 k 17½55xx1 k 175x55xx1 10x10 3/5 k 174x54x1 k 174x54x1 14x14x5 k 175x55x1 94x13 k 154x14x1	74 X34 O4 201A O4 201B 201B O4 201A01B 201B	1090 830 570 1230 1280 1700 1390 850 3750	1.69 2.10 2.10 1.61 1.81 1.82	5 C9 is rotary Dial, C11 6 Avail with Rev. Ch. 0 For Originate Only 2 For Auto Ans or Priv L1 7 Strap Sel Rt 2400/1200 7 Selectable 2000/2400 2 Strap Sel Rt 2400/1200
	T4800FA T4800FB 05-4800 05-4801 05-7200 05-9600 05-9601	*****	4800 4800 4800 4800/2400 7200 9600 9600	PH-S PH-S AHYS-S AHYS-S AHYS-S	Voice-C Voice-C Voice-C	FD FD 2 FD/KD 2 FD/HO 2 FD/HD 2 FD/HD 2 FD/KD	Man. Auto Auto Auto Auto	Cab, Rac Cab, Ra, Cab, Ra,	k " k 12x23x10 k 10x20x2 N 19x23x11 H 19x23x11 K 9x19x21	Ko	4000 4000 4000 5200 6000 9600 9600	1.2	0 Remote Equal 2 Remote Equal 2 40 ma Start-up Time 2 20 ms, Push sel Speed 0 Push Select Speed
Sanders Assoc. Inc. Digital Comm. Den. Webster Ihm Hashwa II.H. 603-885-2011	Series JA Series 12A Series 16A Series 24S Ser 123/31 Ser 24D	H	0/390 0/1200/5/15 0/1800 2400 4020/156/14150/13 2490/1200	PH-S F	Yolce Yolce Yo-C1-1800 Priv. C2-240 Yolce Uncon	FD FD/HD FD/HD FD HD	No Compro Compro Compro Comp Compro	Pac ,Rac Yes	ik 104x11x 74x84 104x114	103 202CDER 202D/0 201B	296-70 296-61 296-61 890-14 307-61 1500-19	20 2	5.1 Tester 101 2.7 1.0 150 one dir-1200 ather .25 All Hodems digital
Singer Tele- Signal 250 Crossways Pk. Dr.	881C 883P 898C	H	0/200 1000/1200 2000,2400 0/1800	FH-A PH-S FH-A	Voice Voice Vo-1200	\$ \$ \$	No Man Han	Cab, Ye	11213x6 12 3x8x14 3x8x14	201A,B	495 680-7	95 3.	40 Opt. 3rd Cd Prov RS232 53
Moodbury, N.Y.	883A 898A	Ħ	0/300 0/1800	PH-A FH-A	Voice Vo-1200 CZ-1800	S S	No Nan	Cab	3x8x14 3x8x14	103A			
Sonex, Inc.	\$83F 31	н	0/300	FH-A	Yaice	FD/HD FD/HD		Cab, Y	3x8x14 es 64x10b es 54x15x1	24 103-113 7 103-113	280 . 2750	1	.07 .09 Price is for 10 Ch.
Telecommunica- tions Div. Stanford, Conn.	703-AC Data Pak 1C	H H	0/300 0/1800 0/150	FH-A FH-A FH-A	Yolce Yolce Yolce Yolce	FU/HD F0/HD F0/HD	Ho Yes No				380 450 329		.79 4.0 4.6
201-325-4161 Yele-Dynamics (div Ambac Ind. \$25 Virginia Or ft, Wash., Pa.	7113-A/8 7113-A/8 7 71036 71036 71037 7202-0/C	H H H H	0/150 0/300 0/300 0/300 0/1800 2000/2400	FH-A FM-A FM-A FM-A FM-S	Yolce Yolce Yolce Yolce Yolce Yol200 C2-1800 Yo-1200	FD FD/HD FD/HD	No No No Opt. Comp	Cab, Y	es 65x94 es 35x19x es 35x19x es 35x194 y 35x194	201-A	98 580 450 0304 E382 8 850	:	s.O7 Card for TIP .52 Auto Ans & Send .67 Man Ans & Send .95 4.7 2.82
Tel-Tech Corp. 11810 Parklaim Rockville, Hd. 201-770-6170	11103 11202 11201 - A/B 11202 - B 112432 1134-1 114-2 114-3 114-48 114-72	5 H H H H H H H H H H H H H H H H H H H	0/100 0/1200 2300/2400 2400 2400,3200 1800/4800 2400/6400 3600/9600 2400-3200 3600/9600	FII-A FII-A FII-S FII-S FII-S FII-S FII-S FII-S	Voice Yoice Yoice Yolce Yolce-Prive Voice-Prive Voice-Prive Voice-Prive Prive Prive	te te te	No No Yes Yes Yes Auto Auto Auto Auto	Cab, Ra Cab, Ra Cab, Ra Cab, Ra Cab Cab Cab	i.V	103 202 201-A/ 201B	Na Na Na Na Na Na		

34 | TELEPHONE ENGINEER & MANAGEMENT, JANUARY 1, 1973

	1000	PODDVACOUSTIC COUPLER	SPEED- HIN/PAX	HODILATION SYNCH-ASYNCH	CHANNELL	DUPLEX/SIPPLEX	BUILT-IN EQUALIZATION	HOUNTING/ OEN CARD AVAILABLE	DIMENSIONS (Inches)	COMPATIBLE W/BELL	PRICE BITS/SECOND	/DOLLAR FEATURES
International Communication Corp. (a Milgo Co.) 7820 H.W. 18th Hisel, Fla. 305-830-4550	2230/20 \$2200/24 3300/36 4500/48 4600/48 4600/72 5500/96 1100 24LSI	н н н н н н	2000max 1200/2400 7400/3600 4800max 4800max 4800/2600 4800/230,40 2400max	PH-S PH-S AMSPH-S AMSPH-S AMSPH-S AMSPH-S OUT phase-S PM-S	Voice Voice Voice Voice Voice Voice C Special	2 FO	Compre. Auto	Cab.Rack Cab.Rack Cab.Rack Cab.Rack Cab.Rack Cab.Rack Cab.Rack Cab.Rack	3x16x15 8x15x10 5'3x18x18 6x16x18 6x18x19 6x18x18 3x6x5	2018 No No No No No	\$1780 (53)1. 1780 (53)1. 3620 (95) 1. 4980 (95) 1. 4750 (85)1. 6900(145)1. 9750(235) 2300/7800 (75/85) t0	35 Strap to CCIT .0 15U Reverse Ch, 96 Com (2) 2400 Ch, 01 Both ends add from 1 site 4800 Backup UDD, Com (3) 4800 Backup UDDD Pair or Coax 82
Intertel, Inc. 6 Yine Brook Ph. Burlington, Pass 617-273-0950	20LS1 1035E 1039F 1039F 2020C 2021C 20280 20108 2011A 2012C	Н В В Н Н Н Н Н Н В В	0/300 0/300 0/300 0/300 0/1200 0/1200 0/1800 0/2400 0/2400 0/2400	FM-A FM-A FM-A FM-A FM-A FM-A FM-S FM-S	Yoice Yoice Yoice Yoice Yoice Yoice-Taice-Taice Yoice Yoice	FD FD FD HO HO	Rompro. Compro.	Yes		20209 202010 2020 2018	350 1 350 1 500 3 600 2 500 5 1325 2	35 Nodem Self Test-LSI Tech. 12 Hodem Self Test-LSI Tech. 14 4 4 7 7 8 8 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
Livermore Gata Systems 2050 Research Or. Livermore, Ca. 415-447-2252	6 C 718 71C 71E 71F 71H 71J	A A A DAA DAA A/DAA A/DAA	0/300 0/300 0/300 0/300 0/300 0/300 0/100 0/100	FM-A FM-A FM-A FM-A FM-A FM-A FM-A	Voice Voice Voice Voice Voice Voice Voice Voice	HO/FO HO/FO HO/FO HO/FO HO/FO HO/FO HO/FO	No No No No No No No	Cab, Yes Cab, Yes Cab, Yes	104x44x84 11x8x6 11x64x44 11x64x44 11x64x44 11x64x44 11x64x44	103/113 103/113 103/113 103/113 103/113 103/113 103/113	\$250 \$1 360 235 1. 325 290 1 350	.2 Mainut Case 34 Mainut Case 28 Plastic Case 32
Hegnavox Re- Search Labs Torrance, Ca. MI ² Data Systems inc. Design Elements, Oivision 1356 Morton Ave. Columbus, Ohio	1X180 AX170B 76-1 88 101CH 103 103CFH 1200	н А/н Н Н Н Н	to 19 mil. 1200,2400 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300	FH-A FH-A FH-A FH-A FX-A	Yoice Yoice Yoice Yoice Yoice Yoice	FD/KD FD/KD FD/KD FD/KD FD/HO FD/HO FO/150	No No No No Yes	Desk,Yes Cab, Yes Cab, Yes Cab, Yes Oesk,Cab		101/103		Yery Hi Speed for Satallite channels Auto. Ans DAA opts. Fits in Teletype origi/auto Ans. Origi/auto Ans. Desk top version of 103 Inc. 150 & 10 b rev. ch,
list' Hideo Ind. Trenton, H.J. Movation 18664 Topham St. Farzena, Ca. 213-344-7191	ADC-300 TH,OC EC-300A,AU ATH,ACM 202	H	0/300 0/440 0/400 0/400 0/1800	FH-A FH-A FM-A FM-A	Voice Voice Yolce Yolce Voice/C2	HO/FO/ HO/FO FO HO/FO HO/AD	S No No No No No Yes	Cab, Yes Cab, blt. in yes Card Cab, Yes Gab/Card			340 2	B- 2 15- Ans. send, configur, 5 4 Teletype built in
GK1-Elec. Ind. 875 Ave. of Amer. New York, II.Y. 212-868-9540/1	201 841065 841066 841068 841092 7018	H H H	2000/2400 0/200 0/200 0/1200 2400	DPSK PN-A FN-A FM-A PR-S	Yaice/CZ Yaice/4W Yaice Yaice Yaice	HD/FD HD/FD/4 HD/FD/4	Yes No Compre. Compre.	Cab/Card Cab Cab Cab	12x15x3 7x114x16 7x114x16 7x114x16 7x114x16 7x114x16	201A/1	\$ 770 \$.2 \$ 770 \$.2 890 .2 940 1.2 2000 1.	0 Custom MOS 6 2 8
(A Hytronics Corp.) Phoenix, Ariz.	701C 701D 702A	N/A N/A N/A N/A A/M	0/450 0/150 0/300 0/300 0/300 0/300 0/600	FH-A FH-A FH-A FH-A FR-A FX-A	Yolce Yolce Yolce Yolce Yolce Yolce N/A	HD/FO HD/FO HD/FO HD/FO HD/FO HD/Fd FD	No No No No No No	Cab Built in Built in Cab Cab Cab, blt in	6\x6\x12 6x3x]] 8x4x]] 8x4x]] 6x4x]] 1148x4	103A2 103A 103A 103A	310 245 295 365 445 335 130-465	
Paradyne Corp. 8550 Ulmerton Largo, Fla. 813-436-4771	H-48 PIX-600 BISY-HC-48 HARG-48	N K P	4800/4800 4800/4800 4800/4300 4800/4300	A1-S A1-S A1-S A1-S	Yalce Yalce Valce Valce	HO/FO HO/FO HO/FD HO/FD	Auto Adapt.	Cab,Rack (Cab,Rack (Cab,Rack (Cab,Rack (β4x17x19 β4x17x19	No No No	\$4250 \$1 6450 6450 5950	.13 Yo Adp Prov Yo .75 Parallel Adapter .75 Built in error Cont.
Penril Data Communications Inc. 5520 Amendolph Rockyllle, Nd. 301-881-8151	POCJOA2 1147-300 POC-311A POC-311B POC-311B POC-311B POC-310F POC-300F POC-1200/19 POC-1200/19 POC-3200F P		0/100 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/300 0/1200	FH-A FH-A FH-A FH-A FH-A FH-A FH-A FH-S FM-S QM-S	Mn No Yolce C2 Yolce Private Yolce Private	HOVED	No N	. 6	rd 45:16 (5:10:10	103/2/ 1016/1 113/10 113/10 113/10 103/11 103/11 103/11 103/12 202C 202D 202D 202D Mo No No	94-18 134-20 31 135-20 31 114-18 13 150-22 3 75 150-22 290-55- 400-62: 170-47: 250-55- 150-11:	0 1.2 Auto Answer 4 1.2 Off-Send Only 9 2.2 Oth-Send Only 9 2.2 Oth-Only 0 2.2 100/2-0-1g 0 2.2 100/2-0-1g 5 2.0 Centra Site 4.0 Oth-Send Only 4.0 Oth-Ans-Only 5 2.0 Maltidrop Polled Sys. 9 4.1 5 Bit Reverse Ch. 5 1.0 150 Bit Reverse Ch. 10.6

Continued on next page

Continued on next page
JANUARY 1, 1973, TELEPHONE ENGINEER & MANAGEMENT | 33

Appendix III

235 Harket St.	1631 1033A 1033A 1033A 1042F 1042F 1042F 1042A 1042A 1047A 1057AA 1075AA 1075AA 1075AA 1176 1177 1177 1188 1098	н н н к н к к н н н к к н н к к	0/300 0/300	HI-A PH-A PH-A FH-A FH-A FH-A PH-A PH-A PH-A PH-A PH-A PH-A PH-A P	Yoice	FO/HO FO/HO FO/HO FO/HO FO/HO FO/HO FO/HO FO/HO FO/HO	Ho Ho Ho Ho Ho Ho Ho Ho Ho			103 103 103 103 103 103 103 103 103 103		Up to 40 Rack Auto Ant Ans Only Orig Only Ans Only Ans Only Ans Only Ans Duly In Dia TP Inter 103AZ/103EZ Auto Ans Priv Ket Up to 40/Rack Auto Ans/Orig Up to 40/Rack OCH-TTI Logic Special Interface Special Inte
Tycom Sys. Corp. Pompton Lakes, NJ 201-839-3000	900	ŅΗ	0/300	FX-A	Yo ice	FD/HD	Ho	Card,Yes	4x9	103A2 103E/F	Cd.69 cou.90	4,35 103 Orig Only
Tymshare, inc.	Hark Y Hark XY	A +1	110/300	FN-A FN-A	Voice Voice	FD/HO FD/HD		Cab, No Card, No	\qx8\qx4 6x \q	103A 103	475	.63
Univac Blue Bell, Pe.	8543	н	0/9600	DC-A/S	. Private	FD/HD		Cab	10x45x7%	No	600	Short Dist-pt-to-pt
Universal Data Sys., Inc. Hantsville, Ala.	UOS-103 UOS-20255 UOS-20215 UOS-202	11 N H	0/300 0/1600 0/1609 0/1800	FH-A	Yoice Yo-1200 Yo-1200 Yo-1200	FO HD/FD HD/FD HD/FD	Na Comp Comp Comp	Cab ,Re ,1	34x8x10 3ca 6x44 34x8x10 34x8x10	103 202 202 202	395 365-560 675 250-445	.76 4.9 2.68 7.2
University Computing Dellas, Yex	90 91 92	A/H A/H A/H	0/300 0/300 0/300	£Н-А F/S-A FM-A	Voice Voice Voice	FD/HD FD/HD FO/HO	Ho Ho	Cab,Yes Cab,Yes PC-Board	4x4x10	103 103	350 415 120	.86 Orig Only ,72 Ans/Orig 2.5 IBM LDLA Comp.
Wadie Core.	YA21 54YA23 YA1200	H	0/300 0/1200 0/1800	FH-A FH-A FK-A	Voice Yolce Vo-1200 C2-1800	FD/KD FD/KD	No Yes Yes	Cab,Ra, Cab,Ra, Cab,Ra,	r PC-555g.1 Y	50SCOÉ	350-450 350-500 250-300	
Hestern Union 82 McKee Dr. Mehwah, N.J. 201-529-4600	16018 21218 2247A 2481A 2200/24	H H H	0/600 0/1200 2400 4800 1200/2400	FH-A FM-A PH-S PH-S PH-S	Yolce Yolce	FD/HO FD/HO FD/HO			5x11x9 5x11x9 7x19x18 64x18x18 34x16 3/	5/8 4x15 5/8		